

Premium Daily Use

Conduct a call

You want to make an external external external call: Dial the code number 0 + number.

You want to make an external private call: Dial the code number 19 + number.

You want to make an internal call: Dial the number.

You want to call the operator: Dial code 1 3 (RWTH).

Connect call

If a call is to be forwarded to another subscriber, it is sufficient to dial the number of the new subscriber during the first call. If the called party is free, you can connect the call immediately by replacing the handset.

Of course you have the possibility to wait until the called participant answers and can give him some more information. To connect, simply hang up the handset.

If the called party does not wish to answer the waiting call, the consultation call can be ended with the function key . You are now reconnected to your 1st party.

If the called party is busy, the waiting call must be retrieved with the function key  (end consultation call).

Consultation with another subscriber

During the 1st call, dial the number of the 2nd party. The 2nd party answers (the 1st party is in the waiting position) and you can exchange information.

End the 2nd call with the Consultation key . You are now reconnected to the 1st subscriber.

Redialing

Wenn Sie die zuletzt angerufene Nummer (intern oder extern) nochmals anwählen möchten, brauchen Sie nur die Taste zu drücken. Der Anruf erfolgt automatisch.

If you want to redial the last number you called (internal or external), simply press the key . The call is made automatically.

Short-term number saving

Your call partner (external) does not answer. Before hanging up, press the key . The number is now stored and can be selected again by pressing this key again. This number remains stored until it is either used or a new number is stored.

If you call an internal telephone and your call partner is busy or the call has not been answered, you can initiate a callback. To do this, dial the code number 1. When your call partner has ended his connection or returns to his seat, he receives your callback request and can react accordingly. To cancel the callback request (when busy), press * 3 4 followed by the extension number.

Answer callback requests

You have received callback requests during a call: As soon as you have ended your current call, the first caller who has initiated a callback request is automatically called back from your telephone.

You have received callback requests during your absence: Your message key  lights up



The number of return calls appears in the display.



The name of the 1st caller is displayed.



The next phone number is displayed.



The previous phone number is displayed




for automatic callback



to delete the numbers

Call retrieval (ISDN message memory)

You have received external ISDN calls during your absence. The display next to the button  shows a black bar.



The first number appears in the display.



to query the next number (if there are several)



for automatic callback  to

delete the numbers

Call retrieval (internal message memory)

You have received internal calls during your absence. Your message key  lights up.



The number of messages appears in the display.



The name of the 1st caller is displayed.



The next message is displayed



The previous message is displayed



for automatic callback



to delete the numbers

Note: Please note that the key  may have a "double" assignment. If messages have been received in your voicebox (telesecretary), the voicemail can be listened to or edited first.

Pressing the key  takes you immediately to the list of internal calls.

Name dialing/ETB (Electronic telephone book)

Enter last name via keyboard (at least two letters) and press "Return". Now the complete name is displayed.

Press the Space key to display the phone number. If

there are several names, you have the option:

Down arrow key: Scroll forward in name list Up

arrow key: Scroll backwards in the name list Once

you've chosen a name:



to call

Activating call forwarding



and call number to which call

Call forwarding immediately: Code * 1 1 or
forwarding is to be performed

Call forwarding on busy: Code * 1 2 and call number to which call forwarding is to be
performed 

Call forwarding after time: Code * 1 3 and call number to which call forwarding is to be made 

Call forwarding on busy/by time: Code * 1 4 and call number to which call forwarding is to be performed


Instead of entering a phone number, you can also enter 71 for voice mail.

Deleting call forwarding

* 1 0  (applies to all call forwarding types)

Note: Each call diversion can also be deleted again by entering the introduction code number again (e.g. immediate call diversion can also be deleted again by * 1 1) or overwritten by entering a new call diversion code number.

Telephone lock

Lock phone: * 3 3 

Unlock phone: * 3 3 and password 